## Temperature Controllers

### **MX Hot Runner Controls**







## Injection Molding Temperature Control Systems

Improve your injection molding output...switch to Tempco's MX Hot Runner Temperature Control System

### The MX System includes:

- ➤ Mainframes
- ➤ 2 types of Temperature Control Modules
- ➤ Cables—Heater Power and Thermocouple
- ➤ Wiring Junction Boxes
- ➤ Input Connectors
- ➤ Floor Stands
- Accessories

### Temperature Control Modules .....



**Tempco's IMP Series Module** provides one of the most technically advanced temperature controls available today. IMP modules use state-of-the-art microprocessor-based circuitry to perform all required PID functions. Units have built-in diagnostics and are fully self-tuning. Setpoint temperatures are maintained without the need to manually preset or adjust the control temperature. Merely set the desired temperature and turn the power on. The module will automatically sense the heat-up rate and control any setpoint temperature deviation.

### **Design Features**

- \* PID Control
- \* CompuStep® Soft Start
- \* CompuCycle®
- \* Manual Control

Part Number: TKA20001

### **Specifications**

**Temperature Range:** Ambient to 999°F (535°C)

Sensor Input: Type J thermocouple

Control Accuracy: ±1.0°F (±0.5°C), dependent on

total thermal system

Calibration Accuracy: Better than 0.2% of full scale

Voltage: 240 VAC standard, 120 VAC available Power Output: 15A @ 240 or 120 VAC 50/60 Hz

Output Switch: Internal zero cross triac

Fusing: High speed fuses on both sides of line

**Setpoint Control:** Precision 3-digit pushbutton Manual Power Control: Single turn potentiometer

**Mode Control:** 

3 Positions: Top—Manual mode; Middle—Auto

mode; Bottom-Auto mode with soft start

Tempco's RMB Temperature Control Module represents the state of the art in Hot Runner temperature control technology. Virtually every feature a molder could want is contained in the module. The RMB's flexible microprocessor-based programming allows the user to modify 17 parameters via the front panel. Once entered, the non-volatile memory automatically saves the parameter modifications.

### **Design Features**

- \* CompuStep®
- \* CompuCycle® Soft Start
- \* Easy Start-Up Procedure
- \* High and Low Deviation Alarms
- \* Open Thermocouple Error Programming
- \* Dual Digital Display
- \* Advanced Diagnostics
- \* Current Monitor

Part Number: TKA20005

### **Specifications**

Temperature Range: 32 to 999°F (0 to 535°C)

**Sensor Input:** Type J or K thermocouple, switch selectable

Control Accuracy: ±0.1°F (±0.1°C) dependent on total

thermal system

Calibration Accuracy: Better than 0.2% of full scale

Voltage: 115 to 230 VAC, ±10%

Power Output: 15A @ 240 or 120 VAC 50/60 Hz

Output Switch: Internal zero cross triac

**Fusing:** High speed fuses on both sides of line

Setpoint Control: two buttons—up and down

Manual Power Control: two buttons—up and down

**Mode Control:** 

3 LEDs: Top/Manual mode

Middle-Auto mode

Bottom-Auto mode with soft start



# Temperature Controllers



**MX Hot Runner Controls** 

Improve your injection molding output...switch to Tempco's MX Hot Runner Temperature Control System



#### **Mainframes**

The configurations illustrated below provide a wide selection of zone capacities to suit almost any control application. The 5, 8 and 12 zone frames use individual frame sections. The 16 through 48 zone frames use 2, 3 or 4 frame sections rigidly fastened together into one prewired integral unit which requires only one main AC power input connection.



### **Mainframe Zone Configurations**

## **Ordering Information**

The following mainframes are set up for 15 Amp per zone IMP or RMB control modules, 240 VAC 3-phase 60 Hz power input. Other power configurations are available; consult Tempco for more information.

Standard lead time is 3 to 4 weeks.

Description	Standard
5-Zone	TKA21005
8-Zone	TKA21008
12-Zone	TKA21012
16-Zone	TKA21016
20-Zone	TKA21020
24-Zone	TKA21024
28-Zone	TKA21028
32-Zone	TKA21032
36-Zone	TKA21036
40-Zone	TKA21040
44-Zone	TKA21044
48-Zone	TKA21048



**Note:** To order a complete Hot Runner Control System the following must be ordered separately:

- ☐ Control Modules
- **■** Mainframe
- ☐ Power Mold Cable
- ☐ Thermocouple Mold Cable
- ☐ Mold Wiring Junction Box (if required)

		Zone Configurations
5-Zone	36-Zone	
8-Zone		
12-Zone		
16-Zone	40-Zone	
20-Zone		
24-Zone		
28-Zone	44-Zone	
32-Zone	48-Zone	

▲ WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov.

### **MX Hot Runner Control Accessories**





## **Injection Mold Temperature Control Systems**

### **Mold Cables**



#### **Power Cables**

Used to connect the mainframe to the hot runner injection mold for heater power.

Number of control zones	10 ft.	20 ft.
5-Zone	TKA22105	TKA22205
8-Zone	TKA22108	TKA22208
12-Zone	TKA22112	TKA22212



## **Thermocouple Cables**

Used to connect the mainframe to the hot runner injection mold for thermocouple signal.

Number of control zones	10 ft.	20 ft.	
5-Zone	TKA23105	TKA23205	
8-Zone	TKA23108	TKA23208	
12-Zone	TKA23112	TKA23212	

### **Mold Connectors**



### **Power Connector**

Used to connect the heater wiring to the power mold cable. Mounts directly on the mold or a wiring junction box.

Part Number		
5-Zone	TKA24005	
8-Zone	TKA24008	
2-7one	TK 424012	







### **Thermocouple Connector**

Used to connect the thermocouples to the thermocouple mold cable.

Mounts directly on the mold or a wiring junction box.


separately.

Part Number TKA25001

Part Number		
	5-Zone	TKA24105
	8-Zone	TKA24108
	12-Zone	TKA24112

## **Mold Wiring Junction Boxes**







for Thermocouple Input Connectors

.

Mold Wiring Junction Box for Thermocouple Input Connectors

Mold Wiring Junction Box for Power Input Connectors

(for 5-, 8- or 12-zone connectors)

Part Number "X" "Y"

4.250"

Zones	Part Number	"X"	"Y"
5	TKA25005	4.250"	4.875"
8	TKA25008	4.990"	5.614"
12	TKA25012	6.052"	6.676"

### Combination Mold Wiring Junction Box for Thermocouple and Power Input Connectors

Mold Wiring Junction Boxes are mounted directly

on the injection mold. The heaters and thermocouples are wired to the connectors and are ordered

4.875"

Zones	Part Number	"X"	"Y"
5	TKA25105	8.031"	8.655"
8	TKA25108	8.843"	9.467"
12	TKA25112	9.906"	10.530"

for Thermocouple and Power Input Connectors